



CURRENT SENSOR

PRODUCT SERIES: STB-LF/2

PRODUCT PART NUMBER: STB-500LF/2

VERSION: Ver 1.2



Sinomags Technology Co., Ltd.

Web site: www.sinomags.com

CONTENT

1.	Description	2
2.	STB-500LF/2 Electrical parameters	3
3.	Dimensions:	4

1. Description

STB-LF/2 series current sensors are based on close loop principle. The sensor can detect the current with DC, AC, pulse and irregular wave shape with current output.

Typical application

- Windmill inverters
- Test and measurement
- Battery supplied applications
- Static converters for DC motors drives
- AC variable speed and servo motor drives
- Switched model power supplies (SMPS)
- UPS

General parameters

Parameter	Symbol	Unit	Value
Supply voltage (-10°C...70°C)	Vcc_max	V	±18
Sensor operating temperature	T _A	°C	-10 ~ 70
Storage temperature	T _S	°C	-25 ~ 80
Mass	m	g	320

Isolation parameters

Parameter	Symbol	Unit	Value	Remark
RMS voltage for AC test 50Hz/1 min	U _d	kV	4.95	
Impulse withstand voltage 1.2/50μs	U _w	kV	9.1	
Clearance distance (pri. -sec)	d _{CI}	mm	25	Shortest distance through air
Creepage distance (pri. -sec)	d _{Cp}	mm	11.5	Shortest path along device body
Case material	-	-	V0	According to UL 94
Comparative tracking index	CTI		275	

2. STB-500LF/2 Electrical parameters

Condition: $V_{cc} = \pm 15V$, $T_A = 25^\circ C$, $R_M = 1\Omega$ unless specified.

Parameters	Symbol	Unit	Min	Typ	Max	Remark
Primary nominal RMS current	I_{PN}	A		500		
Primary current measuring range	I_{PM}	A	-800		800	
Secondary nominal RMS current	I_{SN}	A	-0.1		0.1	
Secondary current	I_s	A	-0.2		0.2	
Resistance of secondary winding	R_s	Ω			8.5	
Supply voltage	V_{cc}	V	± 15		± 18	
Current consumption	I_{cc}	mA		$30 + I_s$		
Turns ratio	N_s	NT		5000		
Overall accuracy @ $25^\circ C$	X_G	%	-0.4		0.4	
Offset current	I_o	mA	-0.13		0.13	
Magnetic offset current	I_{OM}	mA	-0.14		0.14	
Offset current temperature drift	I_{OT}	mA		± 0.15	± 0.64	$-10^\circ C \sim 70^\circ C$
Sensitivity error	ξ_s	%	-0.15		0.15	
Linearity error	ξ_L	% of I_{PN}	-0.1		0.1	
RMS noise current referred to pri.	I_{no}	mA		20		1Hz to 100kHz
Delay time @ 10 % of I_{PN}	$t_{ra\ 10}$	μs		0.5		@10% of I_{pn}
Delay time @ 90 % of I_{PN}	$t_{ra\ 90}$	μs		1		@90% of I_{pn}
-3 dB band width	BW	kHz		100		

3. Dimensions:

